





# LVDS to analog Interface board

## Compact. Versatile. Cost-efficient.



Twiga's interface board easily converts LVDS signals from Sony or Tamron zoom block camera to **analog HD (1080p30)** or **SD (PAL/NTSC).** Choose letter box or crop for the best aspect ratio.

Its **ultra compact** form factor ensures **easy integration** for industrial, medical or drone applications. This board offers a smart and cost-effective solution for adding analog or HDMI output to your project.

Compatible with Sony's and Tamron's zoom block camera range, including the latest Sony FCB-EV9520L & Tamron MP3010.



### LVDS to analog

### **KEY FEATURES**

- HD analog video output: Component video (YPbPr)
- SD analog video output: Composite video (CVBS), S-Video (Y/C)
- Video resolution up to 1080p30
- Automatic LVDS camera video format detection
- Multiple format possibilities: Letter box, Squeeze, Crop
- Communication: UART RS232 or TTL
- Camera output video format configuration by DIP switches



| FUNCTIONS                     | SPECIFICATIONS   |
|-------------------------------|--|
| HD analog video output        | 720p50/60, 1080p25/30 (YPbPr)                          |
| SD analog video output        | PAL with 1080p25/50, NTSC with 1080p30/60 (Y/C - CVBS) |
| Analog video output connector | Molex  |
| Camera control                | VISCA commands via UART RS232 (default) or TTL         |
| GPIOs                         | Camera commands  |
| Power supply                  | 8 to 12 VDC  |
| Operating temperature range   | 0°C to 60°C  |
| Storage temperature range     | -20°C to 60°C  |
| Regulation                    | CE EMC compliant, PCB: UL 94 V0                        |
| Dimensions (mm)               | 55(H) x 41.5(W) x 7(D)                                 |
| Weight                        | 13g  |

### **Ordering information**

| PART NUMBER (P/N) | DESCRIPTION   |
|-------------------|---|
| TV10 0071         | LVDS to analog interface board  |
| TV50 0015         | Mounting kit - Includes: 30-way USL20-30SS-012-C cable assembly, 10-way cable for power supply/UART TTL/Analog output, 3-way cable for RS232, 7-way cable for GPIOs, screws & plastic spacers |

### **Need a custom version?**

We support **tailored solutions** based on your system's layout, connector positions, or special commands. Let's talk about your integration!

### **About i2S | Twiga**

For over 45 years, i2S has been a leading expert in high-quality image capture and processing. In 2023, i2S expanded its expertise by acquiring Twiga, a global specialist in video acquisition, transmission and processing.

Today, i2S partners with customers on complex imaging projects, applying its knowledge across various fields, including industry, heritage digitization, underwater imaging, and health & wellness.



